16A Mobile Electric Car Charger LCD 1.3-Inch Display Screen LED Indicator Light Home New Energy Vehicle Charging Gun

Basic Information

- Brand Name:
- Model Number:

TIANJIN TOEC HUADIAN TECHNOLOGY CO., LTD HD-AMB107



Product Specification

- Plug Model:
- Product Type:
- Shell Material:
- Equipment Size:
- Installation Method:
- Install Components:
- Wiring Method:
- Equipment Weight:
- Highlight:

- NEMA 5-15P
- Plug And Charge
- Gun Head Control Box PC9330
 - Gun Head 230 * 98 * 58mm/control Box 220 * 98 * 62mm [H * W * D]
- Floor/wall Mounted
- Wall Mounted Screw Accessories

Up In And Down Out

- : About1.92KG
 - 16A mobile electric car charger, LCD mobile electric car charger, LCD 16A mobile ev charger

Product Description

We usually export large quantities to foreign countries. Hope to find more trade partners.

Product Name: 16A LCD 1.3-inch Display Screen LED Indicator Light Home New Energy Vehicle Charging Gun

Product Description

Quick Details

1. Portable household portable charger

- 2. After charging and use, it can be carried with the vehicle
- 3. The power of the device is as low as 3W in the on-machine state, saving energy and low consumption
- 4. Three color charging indicator light, indicating charging related values
- 5. Numerical screen display, displaying real-time charging data of the charging gun

Describe

The HD-AMB107 charging gun is a portable charging product that meets the American AC power standards, with a rated maximum AC output power of 1.92KW and a weight of approximately 2KG. It is suitable for household new energy on-board chargers, outdoor travel, emergency relief, outdoor work, and other occasions. -般 格

一般 格		
Detailed parameters		Parameter Details
Name and model		HD-AMB107
	plug model	NEMA 5-15P
Appearance structure	product type	Plug and Charge
	Shell material	Gun Head - Control Box PC9330
	Equipment size	
		Gun head 230 * 98 * 58mm/control box 220 * 98 * 62mm [H * W * D]
	Installation method	Floor/wall mounted
	Install components	Wall mounted screw accessories
	Wiring method	Up in and down out
	Equipment weight	About1.92KG
	Cable specifications	3*2.5mm²+0.75mm²
	Cable length	5 meters [supports customized line length]
	input voltage	AC120V
	Input frequency	50Hz/60Hz
	maximum power	1.92KW
Electrical	output voltage	AC120V
indicators	Output current	16A
	standby power	3W
Environmental indicators	usage scenarios	Indoor/Outdoor
	Working humidity	5% -95% non condensing
	working temperature	-30 +50
	Working altitude	
		Gun head IP67/control box IP67
	Cooling method	Natural cooling
	Safety	
	regulations and	SAEJ1772
	standards	
	Flame retardant	UL94 V0
	grade Product	
	Certification	
Functional	man-machine interface	LCD 1.3 inch display screen/LED indicator light
	communication	
design	interface	Y

for more products please visit us on outdoorpower-station.com

Packaging specifications	Box gauge/weight	505*505*298mm
safety design	Undervoltage protection, overvoltage protection, overload protection, overcurrent protection, over temperature protection, leakage protection, grounding protection, lightning protection, electrostatic protection, flame retardant protectionretardant protection	

Matters needing attention

1. Do not put the product into water!

2. Do not heat the product or approach a fire source! Do not disassemble or modify the product without authorization! Do not forcefully strike the product! otherwise It may cause other hazards such as overheating, short circuit, fire, functional failure, and shortened lifespan of the battery.

- 3. Disassembly and assembly prohibited
- 4. It is prohibited to use non dedicated vehicles for charging, as it may cause danger;

5.If there is leakage, do not directly touch the leakage. The leaked electrolyte can cause skin discomfort. In case the electrolyte enters the eyes, rinse with clean water as soon as possible, do not rub the eyes, and promptly seek medical attention;

Application

Suitable for charging anytime and anywhere in situations such as emergency electricity for American standard new energy vehicles, outdoor travel, emergency relief, and outdoor work.

Frequently Asked Questions

- 1.Can I place a sample order for a charging gun?
- 2. What is the delivery time?
- 3.Is there a minimum order quantity limit for charging gun orders?
- 4. How to transport the goods and how long will it take for delivery?
- 5. How to process charging gun orders? (Requirements, quotations, samples, deposits, production)
- 6. Is it possible to label?
- 7. How long is the warranty period?
- 8. How to handle faults?



S 13752486626 S huangwei@toec-iot.com S outdoorpower-station.com

No. 6, Mount Taishan Road, Hexi District, Tianjin