

Floor / Wall Mounted Portable Ev Car Charger 32A

Basic Information

Brand Name: TIANJIN TOEC HUADIAN TECHNOLOGY

CO., LTD

Model Number: HD-AMB108



Product Specification

Plug Model: NEMA 14-50PProduct Type: Plug And Charge

• Shell Material: Gun Head - Control Box PC9330

• Equipment Size: Gun Head 230 * 98 * 58mm/control Box 220

* 98 * 62mm [H * W * D]

• Installation Method: Floor/wall Mounted

• Install Components: Wall Mounted Screw Accessories

• Wiring Method: Up In And Down Out

• Equipment Weight: About 3.4KG

• Highlight: Floor Mounted portable ev car charger,

32A portable ev car charger, Wall Mounted mobile ev charger

Product Description

We usually export large quantities to foreign countries. Hope to find more trade partners.

Product Name: 32A LCD 1.3-inch Display Screen LED Indicator Light Household New Energy Vehicle Charging Gun

Product Description

Quick Details

- 1. Portable household portable charger
- 2. After charging and use, it can be carried with the vehicle
- 3. The power of the device is as low as 3W in the on-machine state, saving energy and low consumption
- 4. Three color charging indicator light, indicating charging related values
- 5. Numerical screen display, displaying real-time charging data of the charging gun

Describe

The HD-AMB108 charging gun is a portable charging product that meets the American AC power standards, with a rated maximum AC output power of 7.4KW and a weight of approximately 3.4KG. It is suitable for household new energy on-board chargers, outdoor travel, emergency relief, and outdoor work.

General specifications

| Detailed parameters | | Parameter Details |
|---|--|--|
| Name and model | | HD-AMB108 |
| | plug model | NEMA 14-50P |
| Appearance structure | product type | Plug and Charge |
| | Shell material | Gun Head - Control Box PC9330 |
| | Equipment size | Gun head 230 * 98 * 58mm/control box 220 * 98 * 62mm [H * W * D] |
| | Installation method | Floor/wall mounted |
| | Install components | Wall mounted screw accessories |
| | Wiring method | Up in and down out |
| | Equipment weight | About 3.4KG |
| | specifications | 3*6mm²+0.75mm² |
| | | 5 meters [supports customized line length] |
| Electrical indicators Environmental indicators | , , | AC240V |
| | | 50Hz/60Hz |
| | maximum power | 7.4KW |
| | output voltage | AC240V |
| | Output current | 32A |
| | standby power | 3W |
| | usage scenarios | Indoor/Outdoor |
| | Working humidity | 5% -95% non condensing |
| | working temperature | -30 +50 |
| | Working altitude | |
| | | Gun head IP67/control box IP67 |
| | Cooling method | Natural cooling |
| | Safety regulations and standards | SAEJ1772 |
| | Flame retardant grade | UL94 V0 |
| | Product Certification | UL,FCC |
| Functional design | man-machine interface | LED indicator light |
| | communication interface | / |
| Packaging specifications | Box gauge/weight | 505*505*298mm |

| safety design | Undervoltage protection, overvoltage protection, overload protection, overcurrent protection, over temperature protectionakage protection, grounding protection, lightning protection | |
|---------------|---|--|
| | | |
| | electrostatic protection, flame retardant protectionretardant | |
| | protection | |

Matters needing attention

- 1. Do not put the product into water!
- 2. Do not heat the product or approach a fire source! Do not disassemble or modify the product without authorization! Do not forcefully strike the product! otherwise It may cause other hazards such as overheating, short circuit, fire, functional failure, and shortened lifespan of the battery.
- 3. Disassembly and assembly prohibited
- 4. It is prohibited to use non dedicated vehicles for charging, as it may cause danger;
- 5.If there is leakage, do not directly touch the leakage. The leaked electrolyte can cause skin discomfort. In case the electrolyte enters the eyes, rinse with clean water as soon as possible, do not rub the eyes, and promptly seek medical attention:

Application

Suitable for charging anytime and anywhere in situations such as emergency electricity for American standard new energy vehicles, outdoor travel, emergency relief, and outdoor work.

Frequently Asked Questions

- 1.Can I place a sample order for a charging gun?
- 2. What is the delivery time?
- 3.Is there a minimum order quantity limit for charging gun orders?
- 4. How to transport the goods and how long will it take for delivery?
- 5. How to process charging gun orders? (Requirements, quotations, samples, deposits, production)
- 6. Is it possible to label?
- 7. How long is the warranty period?
- 8. How to handle faults?



TIANJIN TOEC HUADIAN TECHNOLOGY CO., LTD



13752486626





e outdoorpower-station.com

No. 6, Mount Taishan Road, Hexi District, Tianjin