

## AC380V EV Wall Charger Wall Mounted Car Charger 22KW 50Hz/60Hz

### Basic Information

- Brand Name: TIANJIN TOEC HUADIAN TECHNOLOGY CO., LTD
- Model Number: HD-OB206



### Product Specification

- Plug Model: Separate Wiring Without Plug
- Product Type: Swipe Card Activation
- Shell Material: Gun Head - Control Box PC9330
- Equipment Size: Gun Head 230 \* 98 \* 70mm/control Box 268 \* 228 \* 100mm [H \* W \* D]
- Installation Method: Pillar/wall Mounted
- Install Components: Wall Mounted Screw Accessories [can Be Installed With Columns]
- Wiring Method: Up In And Down Out
- Equipment Weight: About 6.2KG
- Highlight: **AC380V EV Wall Charger ,  
EV Wall Charger 50Hz ,  
Wall Mounted Car Charger 22KW**

## Product Description

We usually export large quantities to foreign countries. Hope to find more trade partners.

Product Name: 32A Tri color LED Indicator Light Household New Energy Vehicle Charging Station

Product Description

Quick Details

1. Wall mounted and column mounted charging stations
2. Charging, charging, security and anti-theft measures
3. When the device is in standby mode, the power is as low as 3W, saving energy and low consumption
4. Three color charging indicator light, indicating charging related values
5. Numerical screen display, displaying real-time charging data related to the charging station
6. Optional gold and silver glass panels, supporting customized panels

Describe

The HD-OB206 charging gun is a portable charging product that complies with the European Union's AC power consumption standards, with a rated maximum AC output power of 22KW and a weight of approximately 6.2KG. It is suitable for wall mounted household new energy charging stations and is convenient and fast.

General specifications

Detailed parameters		Parameter Details
Name and model		HD-OB206
Appearance structure	plug model	Separate wiring without plug
	product type	Swipe card activation
	Shell material	Gun Head - Control Box PC9330
	Equipment size	Gun head 230 * 98 * 70mm/control box 268 * 228 * 100mm [H * W * D]
	Installation method	Pillar/wall mounted
	Install components	Wall mounted screw accessories [can be installed with columns]
	Wiring method	Up in and down out
	Equipment weight	About 6.2KG
	Cable specifications	5*6mm <sup>2</sup> +0.75mm <sup>2</sup>
	Cable length	5 meters [supports customized line length]
Electrical indicators	input voltage	AC380V
	Input frequency	50Hz/60Hz
	maximum power	22KW
	output voltage	AC380V
	Output current	32A
Environmental indicators	standby power	3W
	usage scenarios	Indoor/Outdoor
	Working humidity	5% -95% non condensing
	working temperature	-30 +50
	Working altitude	<2000 meters
	Protection level	Gun head IP67/control box IP67
	Cooling method	Natural cooling
	Safety regulations and standards	SAEJ1772
	Flame retardant grade	UL94 V0
	Product Certification	TUV,CE,CB

Functional design	man-machine interface	LCD 1.3 inch display screen/LED indicator light
	communication interface	/
Packaging specifications	Box gauge/weight	505*505*298mm
safety design	Undervoltage protection, overvoltage protection, overload protection, overcurrent protection, over temperature protection, leakage protection, grounding protection, lightning protection, electrostatic protection, flame retardant protectionretardant protection	

#### Matters needing attention

1. Do not put the product into water!
2. Do not heat the product or approach a fire source! Do not disassemble or modify the product without authorization! Do not forcefully strike the product! otherwise It may cause other hazards such as overheating, short circuit, fire, functional failure, and shortened lifespan of the battery.
3. Disassembly and assembly prohibited
4. It is prohibited to use non dedicated vehicles for charging, as it may cause danger;
- 5.If there is leakage, do not directly touch the leakage. The leaked electrolyte can cause skin discomfort. In case the electrolyte enters the eyes, rinse with clean water as soon as possible, do not rub the eyes, and promptly seek medical attention;

#### Application

Suitable for charging anytime and anywhere in situations such as emergency electricity for American standard new energy vehicles, outdoor travel, emergency relief, and outdoor work.

#### Frequently Asked Questions

- 1.Can I place a sample order for a charging gun?
2. What is the delivery time?
- 3.Is there a minimum order quantity limit for charging gun orders?
4. How to transport the goods and how long will it take for delivery?
- 5.How to process charging gun orders? (Requirements, quotations, samples, deposits, production)
6. Is it possible to label?
7. How long is the warranty period?
8. How to handle faults?



**TIANJIN TOEC HUADIAN TECHNOLOGY CO., LTD**



13752486626



huangwei@toec-iot.com



outdoorpower-station.com

No. 6, Mount Taishan Road, Hexi District, Tianjin